

JABRA EVOLVE 40



User Manual



A BRAND BY

© 2014 GN Netcom A/S / GN Netcom US, Inc. All rights reserved. Jabra® is a registered trademark of GN Netcom A/S. All other trademarks included herein are the property of their respective owners.

Made in China

MODEL : HSC017 FNC010 FCC ID: BCE-HSC017 IC: 2386C-HSC017



| 1. | WELCOME4 |
|----|-------------------------------------|
| 2. | JABRA EVOLVE 40 OVERVIEW5 |
| | 2.1 STEREO VARIANT |
| | 2.2 MONO VARIANT |
| 3. | HOW TO WEAR7 |
| | 3.1 LEFT OR RIGHT WEARING STYLE |
| | 3.2 ADJUST THE HEADBAND |
| | 3.3 POSITION THE MICROPHONE |
| | 3.4 STORING THE MICROPHONE |
| 4. | HOW TO CONNECT10 |
| | 4.1 CONNECT TO PC (WITH CONTROLLER) |
| | 4.2 CONNECT TO MOBILE DEVICE |
| | (WITHOUT CONTROLLER) |
| 5. | HOW TO USE12 |
| | 5.1 CALLS |
| | 5.2 MULTIPLE CALL HANDLING |
| | 5.3 BUSYLIGHT |
| 6. | SUPPORT15 |
| | 6.1 FAQ |
| | 6.2 HOW TO CARE FOR YOUR HEADSET |
| 7. | TECHNICAL SPECIFICATIONS16 |

WELCOME


Thank you for using the Jabra Evolve 40. We hope you will enjoy it!

JABRA EVOLVE 40 FEATURES


- Busylight on headset and the Jabra Evolve Link controller
- Discreet microphone boom-arm that integrates into the headband when not on calls
- Connects to multiple devices (smartphone or tablet) with 3.5 mm jack (plug & play)
- Superior music and voice capabilities
- Hi-Fi Sound

2. JABRA EVOLVE 40 OVERVIEW

2.1 STERFO VARIANT




CONTROLLER (JABRA EVOLVE LINK)



2.2 MONO VARIANT



Controller (Jabra Evolve Link)



3. HOW TO WEAR



3.1 LEFT OR RIGHT WEARING STYLE

The Jabra Evolve 40 can be worn on the left or right by flipping the microphone to the other side (270° limit).



3.2 ADJUST THE HEADBAND

Adjust the headband to find the most comfortable fit.




3.3 POSITION THE MICROPHONE

It is recommended to position the microphone close to your mouth (0.5 inches).



The microphone is bendable for personal preference.



3.4 STORING THE MICROPHONE


When listening to music or outdoors, the microphone can be stored in the headband groove.



4. HOW TO CONNECT

4.1 CONNECT TO PC (WITH CONTROLLER)

Fully plug the headset into the controller, and connect the controller to a USB port on the PC.



The headset jack MUST be fully inserted into the controller for the headset to work.

NOTE: When the headset is disconnected from the controller, any active call will be put on hold. To resume the call, reconnect the headset to the controller and manually resume the call on the PC (softphone).


4.2 CONNECT TO MOBILE DEVICE (WITHOUT CONTROLLER)

Plug the headset directly into your mobile device.



NOTE: When plugged directly into a mobile device, the overall call quality (for you and the listener) will be lower than when connected to a PC/tablet using the controller (Jabra Evolve Link).

5. HOW TO USE



5.1 CALLS

| | FUNCTION | ACTION |
|----------|-------------------------------|---|
| | Answer/end call | Tap the Answer/end button |
| | Reject call | Double-tap the Answer/end button |
| | Battery and connection status | Tap the Answer/end button when not on a call |
| | Adjust volume | Tap the Volume up or Volume down button |
| | Busylight on/off | Tap the Busylight button |
| 6 | Mute/unmute microphone | Tap the Mute microphone button |

5.2 MULTIPLE CALL HANDLING

The headset can accept and handle multiple calls at the same time.

| FUNCTION | ACTION |
|--|--|
| End current call and answer incoming call | Tap the Answer/end button |
| Switch between held call and active call | Press and hold (2 secs) the Answer/end button |
| Put current call on hold and answer incoming call | Press and hold (2 secs) the Answer/end button |
| Reject incoming call, when on a call | Double-tap the Answer/end button |

5.3 BUSYLIGHT

The busylight indicator on the headset and the controller indicates to others when you are busy.

MANUALLY TURN BUSYLIGHT ON/OFF

To manually activate the busylight on/off, tap the **Busylight** button on the controller. The busylight can be activated even when you are not on a call.

ENABLE/DISABLE BUSYLIGHT FUNCTION

To enable/disable the busylight function, press and hold (3 secs) **Busylight** button on the controller.



SUPPORT

6.1 FAQ

View the FAQs on Jabra.com/evolve40

6.2 HOW TO CARE FOR YOUR HEADSET

- Always store the headset with the power off and safely protected.
- Avoid storage at extreme temperatures (above 25°C/77°F or below -20°C/-4°F). This may adversely affect the headset.

7. TECHNICAL SPECIFICATIONS

| JABRA EVOLVE 40 HEADSET | SPECIFICATION |
|------------------------------|--|
| Headset weight: | Mono headset 80 g Stereo headset 113 g |
| Controller weight: | 55 g |
| Headset dimensions: | Mono headset L 155.4 mm x W 58.6 mm x H 181 mm Stereo headset L 155.5 mm x W 58.6 mm x H 180.9 mm |
| Controller dimensions: | W 54 mm x H 14 mm |
| Microphones: | Noise cancelling microphone |
| Speaker: | 28 mm Dynamic PureSound speakers (Hi-Fi) |
| Speaker maximum input power: | 10 mW |
| Speaker frequency range: | 70 hz - 20 kHz |
| Cable length: | Controller to PC: 90 mm Headset to 3.5mm jack: 1.2 m |
| Noise reduction: | Up to 98% cancellation using Hybrid Active Noise Cancellation |

| JABRA EVOLVE 40 HEADSET | SPECIFICATION |
|-------------------------|-------------------------------|
| ANC time: | Up to 24 hours |
| Operating temperature: | -10°C to 55°C (14°F to 131°F) |
| Storage temperature: | -20°C to 25°C (-4°F to 77°F) |